

MEXICO 86 OR (KICK N RUN)

29.5.87

WIRING DIAGRAM

SOLDER SIDE	PART SIDE	SOLDER SIDE	PARTS SIDE	
GND	1	GND	1	GND
GND	2	+5V	2	+5V
+5V	3		3	
+5V	4		4	
-5V	5		5	
+13V	6	+12V	6	POST
POST	7	POST	7	
COIN METER B	8	COIN METER A	8	
COIN LOCKOUT B	9	COIN LOCKOUT A	9	
SOUND OUT(-)	10	SOUND OUT (+)	10	4P UP
AUDIO(-)	11	AUDIO(+)	11	4P DOWN
GREEN	12	RED	12	4P LEFT
SYNC	13	BLUE	13	4P RIGHT
SERVICE SW	14	GND	14	4P PASS
TILT SW	15	TEST SW	15	4P SHOT
COIN SW B	16	COIN SW A	16	
SELECT 2P	17	SELECT 1P	17	
2P RIGHT	18	1P RIGHT	18	GND
2P UP	19	1P UP		
2P LEFT	20	1P LEFT		
2P DOWN	21	1P DOWN		
2P PASS	22	1P PASS		
2P SHOT	23	1P SHOT		
	24			
	25			
	26			
+5V	27	GND		
+5V	28	GND		

DIP SW A		1	2	3	4	5	6	7	8	
SELECT	OFF	OFF								
SCREEN INVERSION	NORMAL	OFF								
	INVERSION	ON								
TEST MODE	NORMAL	OFF								
	TEST	ON								
ATTRACT SOUND	PRODUCED	OFF								
	NO PRODUCED	ON								
COIN A	1COIN 1PLAY					OFF	OFF			
	1COIN 2PLAYS					ON	OFF			
	1COIN 3PLAY					OFF	ON			
	1COIN 4PLAYS					ON	ON			
COIN B	1COIN 1PLAY							OFF	OFF	
	1COIN 2PLAYS							ON	OFF	
	1COIN 3PLAY							OFF	ON	
	1COIN 4PLAYS							ON	ON	

DIP SW B		1	2	3	4	5	6	7	8
DIFFICULTY									
EASY(A)-DIFFICULT(D)	B	OFF	OFF						
	A	ON	OFF						
	C	OFF	ON						
	D	ON	ON						
PK-MATCHES									
	2 PER TEAK					OFF			
	4 PER TEAK					ON			
SELECT	OFF					OFF			
NUMVER MATCHES									
	5 TEAK							OFF	
	2 TEAK							ON	
SELECT	ON							ON	
	4COIN 4PLAY							ON	