


Philko

## • OVERVIEW

• PCB CONNECTOR: JAMMA STANDARD


• CRT MONITOR: LANDSCAPESCREEN

• ARRANGING CONTROL PANNEL



- BUTTON 1 ······GUN SHOOT BUTTON
- BUTTON 2 ······MISSILE SHOOT BUTTON
- BUTTON 3 ······THUNDER BUTTON

### • DIP SW POSITION



#### JAMMA STANDARD

SOLDERING SIDE			COMPONENT SIDE
GND	A	1	GND
GND	В	2	GND
+5V	С	3	+5V
+5V	D	4	+5V
N.C.	E	5	N. C.
+12V	F	6	+12V
	Н	7	
COIN COUNTER2	J	8	COIN COUNTER 1
COIN LOCK OUT2	K	9	COIN LOCK OUT1
SP (—)	L	10	SP(+)
N. C.	M	11	N.C.
VIDEO GREEN	N	12	VIDEO RED
VIDEO SYNC	Р	13	VIDEO BLUE
SERVICE SW	R	14	VIDEO GND
N.C.	S	15	N. C.
COIN SW 2	Т	16	COIN SW 1
START SW 2	U	17	START SW 1
2P CONTROL UP	V	18	1P CONTROL UP
2P CONTROL DOWN	W	19	1P CONTROL DOWN
2P CONTROL LEFT	X	20	1P CONTROL LEF
2P CONTROL RIGHT	Y	21	1P CONTROL RIGHT
2P CONTROL PUSH1	Z	22	1P CONTROL PUSH1
2P CONTROL PUSH2	a	23	1P CONTROL PUSH2
2P CONTROL PUSH3	b	24	1P CONTROL PUSH3
N. C.	c	25	N. C.
N. C.	d	26	N. C.
GND	е	27	GND
GND	f	28	GND

# • CONNECTOR TYPE

CR7-56DA-3.96: HIROSE

1168-056-009: KEL

# $\lceil \mathsf{TURTLE} \ \ \mathsf{SHIP} \rfloor \ \ \mathsf{DIP} \ \ \mathsf{SWITCH} \ \ \mathsf{INDEX}$

DIP sw1

CONTENTS	1	2	3	4	5	6	7	8
1 PLAYER / 1 CREDIT 2	OFF ON OFF ON OFF ON OFF	OFF OFF ON OFF OFF ON	OFF OFF OFF ON ON ON					
NORMAL MODE DIFFICULT MODE				OFF ON				
NORMAL SCREEN REVERSE SCREEN					OFF ON			
NOT USED						OFF ON		
DICONTINUE MODE CONTINUE MODE							OFF ON	
NORMAL PLAY TEST PLAY								OFF ON

DIP sw 2

(	CONTENTS	1	2	3	4	5	6	7	8
1 CRED 2 3 4	OIT / 1 COIN / 1 / 1 / 1	OFF ON OFF ON	OFF OFF ON ON	OFF OFF OFF					
1 COIN 2 3 4	/ / 1 CREDIT / 1 / 1 / 1	OFF ON OFF ON	OFF OFF ON ON	ON ON ON					
NO MU:	SIC IN DEMO				OFF ON				
BONUS PLAYER	ONLY 150,000 EVERY 150,000 ONLY 200,000 EVERY 200,000					OFF ON OFF ON	OFF OFF ON ON		
NOT U	SED							OFF ON	
NORMAL MODE TEST MODE									OFF ON



Phiko Corporation

ADD: 10, 3-KA, JONGRO, JONGRO-GU,
SEOUL, KOREA

TELEX:PHILKO K29617

FACSIMILE: (02) 274-2846

TEL: (02) 741-0101 / 744-1128