

A.D.2083 by Midcoin pinout

Typed by Corrado Tomaselli (c.tomaselli78@gmail.com)

Date 10.04.2021

SOLDER		PARTS
+5V	A 1	+5V
+5V	B 2	+5V
-5V	C 3	
	D 4	COIN CTR
	E 5	
P2 START	F 6	COIN 2
P1 START	H 7	
COIN 1	J 8	COIN 3?
	K 9	
	L 10	
	M 11	UP
DOWN	N 12	RIGHT
SHOOT	P 13	LEFT
	R 14	
SYNC	S 15	
	T 16	HYPER JUMP
GREEN	U 17	BLUE
	V 18	RED
+12V	W 19	+12V
SPK1+ (MUSIC/SFX)	X 20	SPK2+ (SPEECH)
GND	Y 21	GND
GND	Z 22	GND