

BRUNSWICK "ASPEN" SWITCH MATRIX

	STROBE 1 RED WIRE PC2-PIN 5	STROBE 2 ORANGE WIRE PC2-PIN 4	STROBE 3 BLACK WIRE PC2-PIN 3	STROBE 4 YELLOW WIRE PC2-PIN 2	STROBE 5 BLUE WIRE PC2-PIN 1
RETURN 1 B BROWN WIRE PC2-PIN 9		S-16 START RESET			
RETURN 1 A ORANGE WIRE PC2-PIN 8	S-17 OUTHOLE BALL RETURN				
RETURN 1 RED WIRE PC2-PIN 10			S-6 SPINNER 10 POINT	S-8 SPINNER 10 POINT	
RETURN 2 PINK WIRE PC2-PIN 7	S-11 ROLLOVER 100 POINT	S-14 ROLLOVER 100 POINT	S-5 TARGET 100 POINT	S-7 TARGET 100 POINT	
RETURN 3 GREEN WIRE PC2-PIN 6	S-10 SPINNER 10 POINT	S-4 THUMPER BUMPER SCORE 1000 POINTS	S-1 ROLLOVER 100 POINT	S-13 SCORE 10 POINT	
RETURN 4 WHITE WIRE PC2-PIN 14	S-2 SCORE 10 POINT	S-3 SCORE 10 POINT	S-12 SCORE 10 POINT	S-9 TARGET 100 POINT	
RETURN 4 T YELLOW WIRE PC2-PIN 12					S-15 TILT

CONNECTOR PC2 IS SWITCH MATRIX AND BONUS LIGHTS

CONNECTOR PC1 IS POWER, COILS, AND CHIME BOX

DRAWN BY KEN LAYTON APRIL 5, 2012