

LAST MISSION

Solder Side		Parts Side		DIP SW 1								
					1	2	3	4	5	6	7	8
GND	1	GND		Game Charge								
GND	2	GND		* Table, Upright								
+5V	3	+5V		(Right Selector)							Not Used	Not Used
+5V	4	+5V		1coin 1credit	OFF	OFF						
	5			1coin 2credit	ON	OFF						
+12V	6	+12V		1coin 3credit	OFF	ON						
	7			1coin 5credit	ON	ON						
COIN COUNTER 2	8	COIN COUNTER 1		* Upright								
	9			(Left Selector)								
SPEAKER (-)	10	SPEAKER (+)		1coin 1credit			OFF	OFF				
	11			2coin 1credit			ON	OFF				
VIDEO GREEN	12	VIDEO RED		3coin 1credit			OFF	ON				
VIDEO SYNC	13	VIDEO BLUE		4coin 1credit			ON	ON				
SERVICE SWITCH	14	VIDEO GND		Sound Without					OFF			
	15			With					ON			
COIN SWITCH 2	16	COIN SWITCH 1		Table Type						OFF		
START SWITCH 2	17	START SWITCH 1		Upright Type						ON		
2P CONTROL UP	18	1P CONTROL UP		DIP SW 2	1	2	3	4	5	6	7	8
2P CONTROL DOWN	19	1P CONTROL DOWN		Number of Player								
2P CONTROL LEFT	20	1P CONTROL LEFT		3 OFF								
2P CONTROL RIGHT	21	1P CONTROL RIGHT		5 ON								
2P CONTROL PUSH 1	22	1P CONTROL PUSH 1		Bonus Point /Every							Not Used	Not Used
2P CONTROL PUSH 2	23	1P CONTROL PUSH 2		30,000,50,000/50,000		OFF	OFF					Not Used
2P CONTROL PUSH 3	24	1P CONTROL PUSH 3		30,000,50,000/70,000		ON	OFF					
	25			50,000,100,000/100,000		OFF	ON					
	26			50,000 Only		ON	ON					
GND	27	GND		Difficulty Normal				OFF	OFF			
GND	28	GND		Difficult				ON	OFF			
				Very Difficult				OFF	ON			
				Top Difficult				ON	ON			

* 8 Way 3 Buttons