
ADJUSTMENT ON GAME PC BOARD (G25 00533A VOLFIED)

CONNECTOR



☆ THE CONTROL OF THIS GAME USES
ONE 4-WAY LEVER AND ONE BUTTON.

SOLDER SIDE		Γ	COMPONENTS SIDE
GND	A	1	GND
GND	В	2	GND
+ 5 V	С	3	+5V
+5V	D	4	+5V
-5V	E	5	-5V
+12V	F	6	+12V (+13V)
POST	Н	7	POST
COIN COUNTER (B)	J	8	COIN COUNTER (A)
COIN LOCKOUT (B)	K	9	COIN LOCKOUT (A)
SPEAKER (-)	L	10	SPEAKER (+)
	М	11	
VIDEO G	N	12	VIDEO R
VIDEO SYNC	P	13	VIDEO B
SERVICE SW	R	14	VIDEO GND
TILT SW	S	15	
(COIN B)	T	16	COIN A
2P SELECT	U	17	1P SELECT
2P UP	V	18	1P UP
2P DOWN	W	19	1P DOWN
2P LEFT	X	20	1P LEFT
2P RIGHT	Y	21	1P RIGHT
2P LASER-CUTTER	Z	22	1P LASER-CUTTER
	a	23	
	b	24	
	С	25	
	d	26	
GND	е	27	GND
GND	f	28	GND

NOTE: AFTER CHANGING THE SETTINGS OF DIP SWITCHES, TURN THE POWER OFF.

♦ SETTING OF DIP SWITCH A

(*) : FACTORY SETTINGS

SETTINGS	POSITIONS	1	2	3	4	5	6	7	8
GAME STYLE	TABLE	OFF							
GAME STILE	UPLIGHT	ON	1						
SCREEN ROTATION	* NORMAL		OFF						
SCREEN ROTATION	REVERSE	1	ON		1				
TEST MODE	* NORMAL GAME			OFF					
TEST MODE	TEST MODE			ON	1				
ATTRACT SOUND	* WITH				OFF				
ATTRACT SOUND	WITHOUT				ON				
	* 1 COIN 1 PLAY			-		OFF	OFF		
PLAY PRICING	2 COINS 1 PLAY					ON	0 6 7		
COIN A	3 COINS 1 PLAY					OFF	ON		
	4 COINS 1 PLAY					ON	UN		
	* 1 COIN 2 PLAYS							OFF	OFF
.AY PRICING	1 COIN 3 PLAYS							ON	Urr
COIN B	1 COIN 4 PLAYS							OFF	ON
	1 COIN 6 PLAYS							ON	"

♦ SETTING OF DIP SWITCH B

POSITIONS		SETTINGS	1	2	3	4	5	6	7	8
GAME DIFFICULTY	*	RANK B	OFF	AFF				************		
EASY (A) →		RANK A	ON	ON OFF						
, ,		RANK C	OFF	OFF ON						
DIFFICULT (D)		RANK D	ON	ON						
BONUS POINTS	* 20K/40K/120K/480K/2,400K PTS.			OFF	OFF					
(1 UP)	50K/150K/600K/3,000K PTS.			ON				OFF		
	70K/280K/1.400K PTS.			OFF	O.V.					
(K=1,000PTS.)	100K/500K PTS.			ON	ON					
	*	3					OFF		1	
NUMBER OF		4					ON	OFF		
PLAYERS		5					OFF	۵,,	1	
	6					ON	ON			
EXPRANATION FOR		JAPANESE			***********			•	1	OFF
GAME RULES	*	ENGLISH								ON

"VOLFIED" SETTINGS OF DIP SWs (for other than North America)

DIP SW- A.

DTI DM-Y				3.	ega eranan				
Settings	Positions	11	2	3	a,	. চ	. 5	. 7	8
Game Style	Table Upright	OFF ON			•		•		
Screen Inversion	Normal Game Inversion		OFF ON			•	,		
Test Mode	Normal Game Text Mode		• •	DEF		- +			
Attract	With Without		•		OFF ON				
Play Pricing Coin Slot - A	1 Coin - 1 Play 2 Coins - 1 Play 3 Coins - 1 Play					OFF ON OFF	OFF.		
Play Pricing	1 Coins - 2 Plays 1 Coin - 3 Plays			7				OFF'	OFF
Coin Slot-B	1 Coin - 4 Plays:	1						OFF	:av

DIP SWI-R:

- Poritions	1	2	3	4	5	6	7	6
Rank-B	14U . NO	OFF						
% -C. + - Ð	OFF ON.	' אט						
Normal			OFF ON	-OFF	/		1	
Hard			OFF ON	- ON-				
3					OFF	-OFF		
<u></u> <u></u> <u></u> <u></u>		•		•==	OFF ON	-òu		
								,
				-				ōFF:
	Range - B " - C " - C " - D Normal East	Rank-B Utt 2 - A 9N: 4 - C OFF ON. Normal East: Hard	Rank-B Utt OFF "-A DN: OFF "-C OFF ON ON Normal East: Hard	Rank-B Utt OFF 1 - A 9N: 1 - C OFF ON ON Normal Easy: Hard Regel Re	Rank-B Utt OFF 2 - A 9N: 3 - C OFF ON Normal Easy: Hard PFF ON	Cank-B 1 - A 1 - A 1 - B 1 - C 1 - C 1 - C 1 - D 1 - ON 1 - D 1 ON 1 OFF 1 ON 1 ON 1 ON 1 ON 1 OFF 1 ON 1 O	Cank-B 1 - A 1 - A 1 - C 1 - C 1 - D 1	Cank-B 1-A 1-A 1-A 1-C 1-C 1-C 1-C 1-C

* Factory Settings: all "OFF" Positions


Note: Details of Bonus Points

		2	3	1.	5
EASY	25,000	40,000	129000	480,000	2400000
HORMAL	59000	13.0000	600,000	3000000	
HARD	70,000	280000	tedana	47-	
HARDEST	100,000	500,000		,,	_ :


图 005



① ENCLOSE IT BY USING THE LASER CUTTER BUTTON AND




② DURING MOVING ON THE GREEN "SHIELD LINE" · · · (BURRIER IS ON)
DURING THE PERIOD FROM THE BEGINNING OF DRAWING
THE RED LASER LINE TO THE COMPLETION OF ENCLOSING · · · (BARRIER IS OFF)




- WHEN THE BARRIER IS OFF. IF AN ENEMY TOUCHES THE PLAYER'S MACHINE OR THE RED LASER LINE, THE PLAYER'S MACHINE EXPLODES.
- WHEN THE ENERGY BLOCK

 IS ENCLOSED, A POWER
 CHIP APPEARS! (THIS MEANS THAT THE PLAYER TOOK IT!



·LASER: THE PLAYER

·TIMER: ENEMIES STOP
MOVING FOR A
LIMITED TIME.



·CLASH: THE FOLLOWER

ARE SWEPT

AWAY!

POWER: THE ENERGY
STOPS
DECREASING
FOR A LIMITED
TIME!!





CUT OFF THE ENERGY FIELD 80% OR MORE!!

