

"War Of The Bugs"

Food and Fun Corp./Armenia Ltd. 1981

(Bally Mfg. PCB)

*	Parts Side			Solder Side	*
	GND A	1		GND	
	GND B	2		GND	
	+5 VDC C	3		+5 VDC	
	+5 VDC D	4		+5 VDC	
	+5 VDC E	5		+5 VDC	
		F			
		H			
	Coin 1 J	8		P2 Up *	
	P1 Down K	9		P1 Up	
	P1 Start L	10		P2 Start	
	P1 Left M	11		P1 Right	
	P1 Fire N	12		P2 Fire *	
	* P2 Left P	13		P2 Right *	
(See Note) *	Table mode R	14		P2 Down *	
	Video Ground S	15		Ground	
	Video Red T	16		Video Green	
	Video Blue U	17		Video Sync	
	Speaker - V	18		Speaker +	
	12 VDC W	19		12 VDC	
	12 VDC X	20		12 VDC	
	GND Y	21		GND	
	GND Z	22		GND	

Note * Ground Pin "R" to activate
Cocktail Mode